



When you power up the meter for the first time, the following pages are displayed in succession.



To define the preliminary configuration, press the SET button for at least 3sec.

**1**  
Select the wiring mode




Press



**3.4.3**=3-phase, 4 wires, 3 currents  
**3.3.2**=3-phase, 3 wires, 2 currents  
**1ph**=single phase

Change the mode using



Confirm with



The mode will flash.

Appuyer 2 fois sur



**2**  
Enter the required FSA




Press



**Available values:**  
500 A / 4 kA / 20kA.

Modify the value using



Confirm with



The value will flash

**The FSA corresponds to the current caliber**  
For  $I \leq 500$  A, choose the **500 A caliber**  
For  $500 \text{ A} \leq I \leq 4 \text{ kA}$ , choose the **4 kA caliber**  
For  $4 \text{ kA} \leq I \leq 20 \text{ kA}$ , choose the **20kA caliber**

**3**  
Sauvegarder et quitter

For 3sec press



Confirm with

